


















8.2 Parts List
















[TOP](#) [PREVIOUS](#) [NEXT](#)


Ref. No.	Part No.	Part Name & Description	Remarks
CAPRISTORS			
CRA801	TP00842-51	TAPING GAP TERMINAL	
CRA802	TP00842-51	TAPING GAP TERMINAL	
CAPACITORS			
C001	ECA1CM470B	CAP,E 47UF/16V	
C002	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C003	ECEA1HKA4R7B	CAP,E 4.7UF-50V	
C005	ECA1CM471B	CAP,E 470UF-16V	
C006	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C008	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C010	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C013	ECA0JM101B	CAP,E 100UF-6.3V	
C014	TCJ2VC1H390J	CAP,C 39PF-J-50V	
C015	TCJ2VC1H120J	CAP,C 12PF-J-50V	
C017	TCJ2VC1H270J	CAP,C 27PF-J-50V	
C018	TCJ2VC1H270J	CAP,C 27PF-J-50V	
C020	ECA0JM331B	CAP,E 330UF-6.3V	
C021	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C025	ECA1HM010B	CAP,E 1UF-50V	
C026	ECA1HM010B	CAP,E 1UF-50V	
C032	ECA1CM331B	CAP,E 330UF-16V	
C033	TCJ2VC1H680J	CAP,C 68PF-J-50V	
C034	TCJ2VC1H680J	CAP,C 68PF-J-50V	
C043	ECA1HM2R2B	CAP,E 2.2UF-50V	
C044	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C047	ECA0JM102B	CAP,E 1000UF-6.3V	
C048	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C052	TCJ2VC1H101J	CAP,C 100PF-J-50V	

C053	ECA1HM010B	CAP,E 1UF-50V	
C201	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C224	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C225	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C226	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C301	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C302	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C303	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C307	ECA1HM0R1B	CAP,E 0.1UF/50V	
C310	TCJ2VC1H390J	CAP,C 39PF-J-50V	
C315	EEANA1E1R0B	CAP,E 1.0UF-25V	
C320	TCJ2VF1H104Z	CAP,C .1UF-Z-50V	
C321	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C322	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C323	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C324	TCJ2VF1H104Z	CAP,C .1UF-Z-50V	
C330	ECA1AM101B	CAP,E 100UF-10V	
C331	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C337	ECA1HM2R2B	CAP,E 2.2UF-50V	
C342	ECA1HM010B	CAP,E 1UF-50V	
C351	TACCV470T50V	CAP,C 47PF/50V	
C352	TACCV330T50V	CAP,C 33PF/50V	
C353	TACCV330T50V	CAP,C 33PF/50V	
C358	ECQB1H473JF3	CAP,P .047UF-J-50V	
C359	ECQM4104KZB	CAP,P .10UF-K-400V	
C368	ECQV1H224JL3	CAP,P .22UF-J-50V	
C370	ECKW3D102KBN	CAP,C .001UF-K-2KVDC	
C371	ECEA1HN010UB	CAP,E 1UF/50V	
C373	ECA2EHG100B	CAP,E 10UF-250V	
C377	ECA1CM221B	CAP,E 10UF-16V	
C401	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C402	TCJ2VB1H102K	CAP,C 1000PF-K-50V	
C403	ECA1HM010B	CAP,E 1UF-50V	
C404	ECA1HM010B	CAP,E 1UF-50V	

C405	ECSF1EE105VB	CAP,E 1.0UF-25V	
C407	ECA1HM220B	CAP,E 22UF-50V	
C409	TCJ2VC1H101J	CAP,C 100PF-J-50V	
C410	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C415	TCJ2VF1H104Z	CAP,C .1UF-Z-50V	
C453	EEUNA1E220B	CAP,E 22UF-25V	
C454	ECA1HHG221B	CAP,E 220UF-50V	
C456	ECQB1104JF3	CAP,P .10UF-J-100V	
C458	ECKR1H221KB5	CAP,C 220PF-K-50V	
C459	ECQB1224KF3	CAP,P .22UF-K-100V	
C460	ECA1VM221B	CAP,E 220UF-35V	
C461	ECA1VM470B	CAP,E 47UF/35V	
C462	ECA1VM221B	CAP,E 220UF-35V	
C463	ECQB1H103JF3	CAP,P .01UF-J-50V	
C465	ECA1CM101B	CAP,E 100UF/16V	
C470	ECQB1H104JF3	CAP,P .10UF-J-50V	
C471	ECQB1H104JF3	CAP,P .10UF-J-50V	
C495	ECQB1H683JF3	CAP,P .068UF-J-50V	
C504	ECQB1H222JF3	CAP,P 2200PF-J-50V	
C505	TCJ2VC1H180J	CAP,C 18PF-J-50V	
C506	ECA1CM471B	CAP,E 470UF-16V	
C507	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C511	ECKR2H271KB5	CAP,C 270PF-K-500W	
C512	ECKR2H152KB5	CAP,C .0015UF-K-500V	
C514	ECA1HMR22B	CAP,E .22UF-50V	
C516	TCJ2VC1H221J	CAP,C 220PF-J-50V	
C519	TCJ2VF1H104Z	CAP,C .1UF-Z-50V	
C535	TCJ2VC1H120J	CAP,C 12PF-J-50V	
C548	ECWH16103JVB	CAP,P .01UF-J-1.5KV	
C549	ECQM6333JZW	CAP,P .063UF-J-100V	
C550	ECA160V33UE	CAP,E 33UF/160V	
C551	ECKW3D102JBR	CAP,C 1000PF-J-2KV	
C552	ECQM6332JZW	CAP,P .63UF-J-100V	
C553	ECWF2754JBB	CAP,M .27UF-J-200V	

C554	ECKW3D102JBR	CAP,C 1000PF-J-2KV	
C555	ECA160V33UE	CAP,E 33UF/160V	
C556	ECWH20152JVY	CAP,P 1500PF-J-2KV	
C557	ECA1CM100B	CAP,E 10UF-16V	
C558	ECKW3D561JBR	CAP,C 560PF-J-2KV	
C559	ECKW3D681KBP	CAP,C 680PF-K-2KV	
C560	ECKR2H102KB5	CAP,C 1000PF-K-500V	
C561	ECQB1H273JF3	CAP,P .027UF-J-50V	
C562	ECKR2H471KB5	CAP,C 470PF-K-500V	
C563	ECA1EM102E	CAP,E 1000UF-25V	
C564	ECKR2H471KB5	CAP,C 470PF-K-500V	
C565	ECA1EM102E	CAP,E 1000UF-25V	
C566	ECKR2H471KB5	CAP,C 470PF-K-500V	
C567	ECA1CM471B	CAP,E 470UF-16V	
C569	ECWF2274JBB	CAP,M .27UF-J-200V	
C570	ECA2EM220E	CAP,E 22UF-250V	
C571	ECKR2H102KB5	CAP,C 1000PF-K-500V	
C572	ECWF2334JBB	CAP,P .33UF-J-200V	
C573	ECQE2474KFW	CAP,P .47UF-K-200V	
C580	ECA1HM4R7B	CAP,E 4.7UF-50V	
C581	ECA1CM471B	CAP,E 470UF-16V	
C582	ECA1CM101B	CAP,E 100UF/16V	
C583	ECA1CM100B	CAP,E 10UF-16V	
C593	ECEA1HNR47UB	CAP,E .47UF-50V	
C595	ECA1HM100B	CAP,E 10UF/50V	
C601	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C603	ECQB1H223JF3	CAP,P .022UF-J-50V	
C616	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C619	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C628	TCJ2VC1H151J	CAP,C 150PF-J-50V	
C632	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C641	ECA1CM100B	CAP,E 10UF-16V	
C701	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C750	TCJ2VC1H181J	CAP,C 180PF-J-50V	

C751	ECQE1335KFB	CAP,P 3.3UF-K-100V	
C752	ECA1VM470B	CAP,E 47UF/35V	
C753	ECQB1H222JF3	CAP,P 2200PF-J-50V	
C754	TCJ2VB1H332K	CAP,C .0033UF-K-50V	
C755	TCJ2VB1H273K	CAP,C .027UF-K-50V	
C756	ECKR2H332KB5	CAP,C 3300PF-K-550V	
C757	TCJ2VB1H332K	CAP,C .0033UF-K-50V	
C763	ECKR3A121KBP	CAP,C 120PF-K-1KV	
C801	ECKWAE472ZED	CAP,C 4700PF-Z-500V	
C802	ECKWAE472ZED	CAP,C 4700PF-Z-500V	
C803	ECKWAE472ZED	CAP,C 4700PF-Z-500V	
C804	ECKWAE472ZED	CAP,C 4700PF-Z-500V	
C805	EC0S2DA561BB	CAP,E 560PF-200V	
C806	ECQB1H104JF3	CAP,P .10UF-J-50V	
C807	ECQB1H473JF3	CAP,P .047UF-J-50V	
C809	ECKR3A472KBP	CAP,C .0047UF-K-1KV	
C812	ECQU2A224MVA	CAP,P .22UF-M-250VAC	
C813	ECQU2A153MVA	CAP,P .015UF-M-250VAC	
C814	ECQU2A153MVA	CAP,P .015UF-M-250VAC	
C815	ECQB1H104JF3	CAP,P .10UF-J-50V	
C816	ECQB1H473JF3	CAP,P .047UF-J-50V	
C817	ECQU2A224MVA	CAP,P .22UF-M-250VAC	
C818	ECQB1H103JF3	CAP,P .01UF-J-50V	
C819	ECKCNB102MB	CAP,C 1000PF-M-250V	
C820	ECKCNB102MB	CAP,C 1000PF-M-250V	
C821	ECA1HM471E	CAP,E 470UF-50V	
C822	ECKR3A821KBP	CAP,C 820PF-K-1KV	
C823	ECA1CHG101B	CAP,E 100UF-16V	
C824	ECKR3A152KBP	CAP,C 1500PF-K-1KVDC	
C825	EEUMG2C221S	CAP,E 220UF-160V	
C826	ECKR3A821KBP	CAP,C 820PF-K-1KV	
C827	ECA1CM102B	CAP,E 1000UF/16V	
C828	ECKR1H471KB5	CAP,C 470PF-K-50V	
C832	ECKR3A471KBP	CAP,C 470PF-K-1KV	

C835	ECA1EM101B	CAP,E 100UF-25V	
C901	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C902	TCJ2VC1H561J	CAP,C 560PF-J-50V	
C904	ECKR1H103ZF5	CAP,C .01UF-Z-50V	
C952	ECA1HM100B	CAP,E 10UF/50V	
C953	ECKR1H103ZF5	CAP,C .01UF-Z-50V	
C958	ECA2CM470E	CAP,E 47UF-160V	
C959	ECKW2H103ZF7	CAP,C .01UF-Z-500V	
C960	ECCR2H151J5	CAP,C 150-500V	
C961	ECA2AM100B	CAP,E 10UF-100V	
C962	ECKW2H103ZF7	CAP,C .01UF-Z-500V	
C963	ECCR1H151J5	CAP DISC 150-5-50V	
C964	ECA1CHG101B	CAP,E 100UF-16V	
C966	ECA1CHG101B	CAP,E 100UF-16V	
C967	ECA1CM221B	CAP,E 10UF-16V	
C968	ECKR1H103ZF5	CAP,C .01UF-Z-50V	
C969	ECKR1H103ZF5	CAP,C .01UF-Z-50V	
C971	TACCW222T50V	CAP,C 2200PF/50V	
C1001	ECA1CM471E	CAP,E 470UF-16V	
C1002	TACCX103T50V	CAP,C .01UF/50V	
C1003	ECA0JM101B	CAP,E 100UF-6.3V	
C1004	TACCX103T50V	CAP,C .01UF/50V	
C1005	TACCX103T50V	CAP,C .01UF/50V	
C2202	ECA1HM2R2B	CAP,E 2.2UF-50V	
C2203	ECA1HM4R7B	CAP,E 4.7UF-50V	
C2204	AP106K016CAE	CAP,T 10UF/16V	
C2205	ECA1HM010B	CAP,E 1UF-50V	
C2206	ECQB1H223JF3	CAP,P .022UF-J-50V	
C2207	AP335K016CAE	CAP,T 3.3UF/16V	
C2208	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C2209	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C2210	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C2211	ECA1CM100B	CAP,E 10UF-16V	
C2212	ECQB1H473JF3	CAP,P .047UF-J-50V	







C2215	ECA0JM101B	CAP,E 100UF-6.3V	
C2218	ECA1HMR47B	CAP,E .47UF-50V	
C2220	TCJ2VC1H100D	CAP,C 10PF-J-50V	
C2302	ECA1HM010B	CAP,E 1UF-50V	
C2305	ECA1HM010B	CAP,E 1UF-50V	
C2307	ECA1EM102E	CAP,E 1000UF-25V	
C2308	ECA1HM101B	CAP,E 100UF-50V	
C2311	ECA1HM010B	CAP,E 1UF-50V	
C2312	ECA1EM102E	CAP,E 1000UF-25V	
C2313	ECA1VM102E	CAP,E 1000UF-35V	
C2314	ECA1CM101B	CAP,E 100UF/16V	
C2331	ECA1HM010B	CAP,E 1UF-50V	
C2332	ECA1HM010B	CAP,E 1UF-50V	
C2333	ECA1EM100B	CAP,E 10UF-25V	
C2334	ECA1EM100B	CAP,E 10UF-25V	
C2335	ECA1HM010B	CAP,E 1UF-50V	
C2336	ECA1HM010B	CAP,E 1UF-50V	
C2337	ECA1CM470B	CAP,E 47UF/16V	
C2431	ECA1HM010B	CAP,E 1UF-50V	
C2432	ECA1HM010B	CAP,E 1UF-50V	
C2433	TCJ2YC1H222J	CAP,C .022UF-J-50V	
C2437	TCJ2VB1H333K	CAP,C .033UF-K-50V	
C2438	TCJ2VB1H102K	CAP,C 1000PF-K-50V	
C2444	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C2445	TCJ2VB1C104K	CAP,C .1UF-K-16V	
C2449	TCJ2VB1H333K	CAP,C .033UF-K-50V	
C2450	TCJ2VB1H102K	CAP,C 1000PF-K-50V	
C2451	ECEA1CN100UB	CAP,E 10UF-16V	
C2459	TCJ2VB1H333K	CAP,C .033UF-K-50V	
C2460	TCJ2VB1H333K	CAP,C .033UF-K-50V	
C2461	ECA1HM4R7B	CAP,E 4.7UF-50V	
C2462	ECA1HM4R7B	CAP,E 4.7UF-50V	
C2463	ECEA1CN100UB	CAP,E 10UF-16V	
C2464	TCJ2VB1H333K	CAP,C .033UF-K-50V	







C2465	TCJ2VB1H333K	CAP,C .033UF-K-50V	
C2468	ECA1AM101B	CAP,E 100UF-10V	
C2473	ECA1HM4R7B	CAP,E 4.7UF-50V	
C2474	ECA1AM101B	CAP,E 100UF-10V	
C2475	ECA1HM4R7B	CAP,E 4.7UF-50V	
C3001	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C3002	ECA1AM101B	CAP,E 100UF-10V	
C3003	ECA1CM100B	CAP,E 10UF-16V	
C3004	ECA1HM010B	CAP,E 1UF-50V	
C3006	ECA1HM010B	CAP,E 1UF-50V	
C3007	ECA1CM100B	CAP,E 10UF-16V	
C3008	ECA1CM100B	CAP,E 10UF-16V	
C3009	ECA1HM010B	CAP,E 1UF-50V	
C3010	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C3011	ECA1HM010B	CAP,E 1UF-50V	
C3012	ECA1CM100B	CAP,E 10UF-16V	
C3013	ECA1CM100B	CAP,E 10UF-16V	
C3014	ECA1HM010B	CAP,E 1UF-50V	
C3016	ECA1HM010B	CAP,E 1UF-50V	
C3018	ECA1CM100B	CAP,E 10UF-16V	
C3019	ECA1CM100B	CAP,E 10UF-16V	
C3020	ECA1HM010B	CAP,E 1UF-50V	
C3021	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C3022	ECA1HM010B	CAP,E 1UF-50V	
C3023	ECA1CM100B	CAP,E 10UF-16V	
C3024	ECQB1H104JF3	CAP,P .10UF-J-50V	
C3025	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C4801	ECA1HM4R7B	CAP,E 4.7UF-50V	
C4803	ECQV1H334JL3	CAP,P .33UF-J-50V	
C4804	ECQV1H334JL3	CAP,P .33UF-J-50V	
C4805	ECA1VM470B	CAP,E 47UF/35V	
C4806	ECA1HM4R7B	CAP,E 4.7UF-50V	
C4808	ECA1HM330B	CAP,E 33UF-50V	
C6501	ECA0JM101B	CAP,E 100UF-6.3V	






C6502	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C6503	TCJ2VF1H104Z	CAP,C .1UF-Z-50V	
C6504	ECA1AM470B	CAP,E 47UF-10V	
C6505	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C6506	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C6507	ECA1HMR47B	CAP,E .47UF-50V	
C6508	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C6509	ECA1CM470B	CAP,E 47UF/16V	
C6510	TCJ2VF1H104Z	CAP,C .1UF-Z-50V	
C6511	TCJ2VF1H104Z	CAP,C .1UF-Z-50V	
C6512	ECA1CM470B	CAP,E 47UF/16V	
C6513	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C6514	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C6515	TCJ2VF1H104Z	CAP,C .1UF-Z-50V	
C6516	ECA1CM470B	CAP,E 47UF/16V	
C6517	TCJ2VC1H181J	CAP,C 180PF-J-50V	
C6518	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C6519	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C6520	ECA1CM470B	CAP,E 47UF/16V	
C6525	TCJ2VC1H120J	CAP,C 12PF-J-50V	
C6526	TCJ2VC1H270J	CAP,C 27PF-J-50V	
C6532	TCJ2VB1H103K	CAP,C .01UF-K-50V	
C6569	TCJ2VC1H180J	CAP,C 18PF-J-50V	
C6570	ECA1HM010B	CAP,E 1UF-50V	
C6572	ECEA1CN470UB	CAP,E 47UF-16V	



DIODES



D001	MA2C165001VT	DIODE	
D002	MA2C165001VT	DIODE	
D003	MAZ40560MF	DIODE, ZENER	
D006	MAZ43300HF	DIODE, ZENER	
D010	MAZ41000LF	DIODE, ZENER	
D014	MA2C165001VT	DIODE	
D015	MA2C700A0F	DIODE	
D051	MAZ40560MF	DIODE, ZENER	

D052	MA2C165001VT	DIODE	
D240	MA2C165001VT	DIODE	
D354	MA2C165001VT	DIODE	
D355	MA2C165001VT	DIODE	
D356	MA2C165001VT	DIODE	
D360	B0HAGP000003	DIODE	
D361	B0HAGP000003	DIODE	
D362	B0HAGP000003	DIODE	
D363	MA2C165001VT	DIODE	
D375	MA2C165001VT	DIODE	
D451	B0EAKM000018	DIODE, RECTIFIER	
D455	MA2C165001VT	DIODE	
D456	MA2C165001VT	DIODE	
D457	MA2C165001VT	DIODE	
D459	MA2C165001VT	DIODE	
D551	B0HAMV000018	DIODE	
D552	B0HAMP000059	DIODE	
D553	MA4062LTVTA	DIODE, ZENER	
D554	MAZ42700MF	DIODE, ZENER	
D556	MAZ43600HF	DIODE, ZENER	
D561	MA2C165001VT	DIODE	
D562	D1NL40V70	DIODE	
D563	B0HAMP000039	DIODE	
D564	B0HAMP000039	DIODE	
D570	D1NL40V70	DIODE	
D575	MA2C165001VT	DIODE	
D580	D1NL40V70	DIODE	
D753	AU01ZV0	DIODE	
D754	MA2C165001VT	DIODE	
D801	GP15KL-042	DIODE	
D802	GP15KL-042	DIODE	
D803	GP15KL-042	DIODE	
D804	GP15KL-042	DIODE	
D806	TAP2AA0001	PTC 5-OHM	



D807	B0HAMM000072	DIODE, FAST RECOVERY	
D808	B0HAMM000072	DIODE, FAST RECOVERY	
D809	MAZ40360MF	DIODE, ZENER	
D810	MAZ41500MF	DIODE, ZENER	
D811	MAZ42700MF	DIODE, ZENER	
D812	B0HAMM000072	DIODE, FAST RECOVERY	
D813	B0BA01000046	DIODE, ZENER	
D814	B0BA01000046	DIODE, ZENER	
D822	B0HANL000004	DIODE	
D823	S3L60P154004	DIODE	
D824	B0HAMM000072	DIODE, FAST RECOVERY	
D825	MA2C165001VT	DIODE	
D826	MAZ41800HF	DIODE, ZENER	
D838	MAZ41500MF	DIODE, ZENER	
D839	MA2C165001VT	DIODE	
D840	B0HAMM000072	DIODE, FAST RECOVERY	
D845	MA2C165001VT	DIODE	
D1001	MAZ40680MF	DIODE, ZENER	
D1002	MAZ40680MF	DIODE, ZENER	
D1003	MAZ40680MF	DIODE, ZENER	
D1005	MAZ40680MF	DIODE, ZENER	
D2302	MA2C165001VT	DIODE	
D2303	MA2C165001VT	DIODE	
D2318	MA2C165001VT	DIODE	
D3007	MAZ41100MF	DIODE, ZENER	
D3008	MAZ41100MF	DIODE, ZENER	
D3023	MAZ41100MF	DIODE, ZENER	
D3024	MAZ41100MF	DIODE, ZENER	
D3025	MAZ41100MF	DIODE, ZENER	
D3026	MAZ41100MF	DIODE, ZENER	
D3027	MAZ41100MF	DIODE, ZENER	
D3028	MAZ41100MF	DIODE, ZENER	
D3029	MAZ41100MF	DIODE, ZENER	
D3030	MAZ41100MF	DIODE, ZENER	

FUSES			
F801	XBA2A00101	FUSE 6.3A 125V	
INTEGRATED CIRCUITS			
IC001	MN101C46FTK	MPU	
IC002	C3EAGC000017	EEPROM	
IC003	PIC-37042SR	IR REMOTE RECEIVER	
IC005	C0CBABC00037	STBY REGULATOR	
IC006	PST9128NR	RESET	
IC101	TA1310DN	VCJ	
IC351	C1AA00000622	RGB OUT AMP	
IC451	C1AA00000521	VERTICAL OUT	
IC551	AN78M09LB	9V REG	
IC552	AN7805LB	5V REG	
IC750	C0AABB000084	HORIZONTAL	
IC801	PC123FY2	OPTO COUPLER	
IC820	C0DAEJC00003	ZENER REG	
IC1001	TC4066BP	INT CKT	
IC2201	AN5849S-E1V	AUDIO AMP	
IC2301	AN5277	VAO AMP	
IC2331	C0AABB000084	SOUND PROCESSOR	
IC2451	BH3868CFS-E2	A/V SWITCH	
IC3001	M52790SP	A/V SWITCH	
IC4801	PUB4301	GEOMAGNETIC CIRCUIT	
IC4802	AN6564	GEOMAGNETIC CIRCUIT	
IC6501	TC90A49P	3L COMB FILTER	
COILS			
J329	EXCELSA39V	FERRITE BEAD	
J338	EXCELSA39V	FERRITE BEAD	
L002	ELESN180JA	COIL, PEAKING 18UH	
L003	G0C2R2KA0021	COIL, PEAKING 2.2UH	
L004	G0C2R2KA0021	COIL, PEAKING 2.2UH	
L005	ELESN330JA	COIL, PEAKING 33UH	
L006	EXCELSA35T	FERRITE BEAD	
L008	G0C101KA0021	COIL, PEAKING 100UH	

L010	G0C2R2KA0021	COIL, PEAKING 2.2UH	
L011	G0C2R2KA0021	COIL, PEAKING 2.2UH	
L012	G0C2R2KA0021	COIL, PEAKING 2.2UH	
L013	G0C2R2KA0021	COIL, PEAKING 2.2UH	
L100	G0C2R2KA0021	COIL, PEAKING 2.2UH	
L146	EXCELSA35T	FERRITE BEAD	
L152	EXCELSA39V	FERRITE BEAD	
L157	G0C101KA0021	COIL, PEAKING 100UH	
L159	G0C470KA0021	COIL, PEAKING 47UH	
L301	G0C470KA0021	COIL, PEAKING 47UH	
L302	ELESN120JA	COIL, PEAKING 12UH	
L319	G0C101KA0021	COIL, PEAKING 100UH	
L519	ELESN101JA	COIL, PEAKING 100UH	
L551	ELH5L6120	COIL	
L553	EXCELSA39V	FERRITE BEAD	
L556	ELC18B801E	COIL	
L559	TLUADNB682K	COIL	
L601	G0C560K00004	COIL, PEAKING 56UH	
L706	EXCELSA35T	FERRITE BEAD	
L751	ELC18B801E	COIL	
L752	TALL13N103JB	COIL	
L801	ELF20N020A	COIL, 2UH	
L802	G0C681Z00001	COIL	
L803	EXCELSA26T	FERRITE BEAD	
L805	TALL08T220KA	TRANSFORMER, LINE FILTER	
L807	EXCELSA39V	FERRITE BEAD	
L808	ELF20N020A	COIL, 2UH	
L809	EXCELSA39V	FERRITE BEAD	
L951	EXCELSA24T	FERRITE BEAD	
L953	EXCELSA24T	FERRITE BEAD	
L954	EXCELSA24T	FERRITE BEAD	
L955	EXCELSA24T	FERRITE BEAD	
L6503	ELESN330JA	COIL, PEAKING 33UH	
L6504	EXCELSA35T	FERRITE BEAD	

L6505	EXCELSA35T	FERRITE BEAD	
L6507	ELESN150JA	COIL, PEAKING 15UH	
L6508	EXCELSA24T	FERRITE BEAD	
L6509	EXCELSA35T	FERRITE BEAD	
TRANSISTORS			
Q001	2SC1685QRSTA	TRANSISTOR	
Q002	2SC1685QRSTA	TRANSISTOR	
Q003	2SD601ARTX	TRANSISTOR	
Q004	2SC1685QRSTA	TRANSISTOR	
Q005	2SD601ARTX	TRANSISTOR	
Q006	2SD601ARTX	TRANSISTOR	
Q007	2SC1685QRSTA	TRANSISTOR	
Q201	2SD601ARTX	TRANSISTOR	
Q303	2SD601ARTX	TRANSISTOR	
Q369	2SA1309ATA	TRANSISTOR	
Q402	2SD601ARTX	TRANSISTOR	
Q453	2SD601ARTX	TRANSISTOR	
Q480	2SA1309ATA	TRANSISTOR	
Q501	2SC3941HTA	TRANSISTOR	
Q515	2SD601ARTX	TRANSISTOR	
Q551	2SC5339LBMA1	TRANSISTOR	
Q603	2SD601ARTX	TRANSISTOR	
Q611	2SB709ARTX	TRANSISTOR	
Q701	2SD601ARTX	TRANSISTOR	
Q751	B1DACM000001	TRANSISTOR	
Q754	2SD601ARTX	TRANSISTOR	
Q801	B1DEGQ000013	TRANSISTOR	
Q803	2SC1318STA	TRANSISTOR	
Q805	2SC1318STA	TRANSISTOR	
Q861	2SB1011QRL	TRANSISTOR	
Q862	2SC1473ATA	TRANSISTOR	
Q901	2SD601ARTX	TRANSISTOR	
Q951	2SC3311ATA	TRANSISTOR	
Q952	2SC3311ATA	TRANSISTOR	










Q953	2SC1741ASTP	TRANSISTOR	
Q954	2SB1030ATA	TRANSISTOR	
Q955	2SB1569AF51E	TRANSISTOR	
Q956	2SD2400AF51E	TRANSISTOR	
Q957	2SA1309ATA	TRANSISTOR	
Q958	2SC3311ATA	TRANSISTOR	
Q961	2SC3311ATA	TRANSISTOR	
Q962	2SC3311ATA	TRANSISTOR	
Q1001	2SC1685QRSTA	TRANSISTOR	
Q1002	2SC1685QRSTA	TRANSISTOR	
Q1003	2SC1685QRSTA	TRANSISTOR	
Q1004	2SC1685QRSTA	TRANSISTOR	
Q1005	2SC1685QRSTA	TRANSISTOR	
Q1006	2SC1685QRSTA	TRANSISTOR	
Q1007	2SC1685QRSTA	TRANSISTOR	
Q1008	2SC1685QRSTA	TRANSISTOR	
Q1009	2SC1685QRSTA	TRANSISTOR	
Q1010	2SC1685QRSTA	TRANSISTOR	
Q1011	2SC1685QRSTA	TRANSISTOR	
Q2301	2SD601ARTX	TRANSISTOR	
Q2302	2SD601ARTX	TRANSISTOR	
Q2303	2SD601ARTX	TRANSISTOR	
Q2331	2SD601ARTX	TRANSISTOR	
Q2332	2SB709ARTX	TRANSISTOR	
Q2333	2SD601ARTX	TRANSISTOR	
Q2334	2SD601ARTX	TRANSISTOR	
Q2335	2SB709ARTX	TRANSISTOR	
Q2336	2SD601ARTX	TRANSISTOR	
Q6501	2SD601ARTX	TRANSISTOR	
Q6502	2SB709ARTX	TRANSISTOR	
Q6506	2SD601ARTX	TRANSISTOR	
Q6510	2SD601ARTX	TRANSISTOR	
Q6511	2SD601ARTX	TRANSISTOR	
Q6512	2SD601ARTX	TRANSISTOR	



Q6519	2SD601ARTX	TRANSISTOR	
RELAYS			
RL801	K6B1AGA00042	RELAY	
RL802	K6B1AGA00042	RELAY	
RESISTORS			
R001	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R002	ERJ6GEYJ182V	RES,M 1.8K-J-1/10W	
R004	ERDS1TJ122T	RES,C 1.2K-J-1/2W	
R005	ERG1SJ680E	RES,M 68-J-1W	
R006	ERJ6ENF1372V	RES,M 13.7K-F-1/10W	
R007	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R009	ERJ6GEYJ221V	RES,M 220-J-1/10W	
R010	ERJ6GEYJ223V	RES,M 22K-J-1/10W	
R011	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R012	ERJ6GEYJ223V	RES,M 22K-J-1/10W	
R013	ERJ6ENF1002V	RES,M 10K-F-1/10W	
R014	ERJ6GEYJ392V	RES,M 3.9K-J-1/10W	
R015	ERJ6GEYJ472V	RES,M 4.7K-J-1/10W	
R016	ERJ6GEYJ472V	RES,M 4.7K-J-1/10W	
R017	ERJ6GEYJ472V	RES,M 4.7K-J-1/10W	
R020	ERJ6GEYJ682V	RES,M 6.8K-J-1/10W	
R021	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R022	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R023	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R024	ERJ6ENF2322V	RES,M 23.2K-F-1/10W	
R025	ERJ6GEYJ223V	RES,M 22K-J-1/10W	
R026	ERJ6GEYJ473V	RES,M 47K-J-1/10W	
R027	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R028	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R029	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R030	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R032	ERJ6ENF1002V	RES,M 10K-F-1/10W	
R033	ERJ6GEYJ272V	RES,M 2.7K-J-1/10W	
R034	ERJ6GEYJ222V	RES,M 2.2K-J-1/10W	



R035	ERJ6GEYJ362V	RES,M 3.6K-J-1/10W	
R036	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R037	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R038	ERJ6GEYJ223V	RES,M 22K-J-1/10W	
R039	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R040	ERJ6GEYJ472V	RES,M 4.7K-J-1/10W	
R041	ERJ6GEYJ472V	RES,M 4.7K-J-1/10W	
R042	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R044	ERJ6GEYJ273V	RES,M 27K-J-1/10W	
R045	ERJ6GEYJ223V	RES,M 22K-J-1/10W	
R046	ERJ6GEYJ333V	RES,M 33K-J-1/10W	
R047	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R048	ERJ6GEYJ333V	RES,M 33K-J-1/10W	
R049	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R050	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R051	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R052	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R053	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R054	ERJ6GEYJ123V	RES,M 12K-J-1/10W	
R057	ERDS2TJ472T	RES,C 4.7K-J-1/4	
R059	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R060	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R061	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R062	ERDS2TJ153T	RES,C 15K-J-1/4W	
R066	ERJ6GEYJ752V	RES,M 7.5K-J-1/10W	
R067	ERJ6GEYJ752V	RES,M 7.5K-J-1/10W	
R068	ERJ6GEYJ752V	RES,M 7.5K-J-1/10W	
R072	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R073	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R074	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R075	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R076	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R077	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R078	ERJ6GEYJ101V	RES,M 100-J-1/10W	

R079	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R100	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R101	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R102	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R122	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R123	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R201	ERJ6GEYJ331V	RES,M 330-J-1/10W	
R223	ERJ6GEYJ561V	RES,M 560-J-1/10W	
R225	ERJ6GEYJ331V	RES,M 330-J-1/10W	
R226	ERJ6GEYJ331V	RES,M 330-J-1/10W	
R245	ERJ6GEYJ224V	RES,M 220K-J-1/10W	
R246	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R301	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R302	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R303	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R306	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R310	ERJ6GEYJ332V	RES,M 3.3K-J-1/10W	
R328	ERJ6GEYJ105V	RES,M 1M-J-1/10W	
R329	ERJ6GEYJ304V	RES,M 300K-J-1/10W	
R341	ERJ6GEYJ474V	RES,M 470K-J-1/10W	
R351	ER0S2THF9100	RES,M 910-F-1/4W	
R352	ER0S2THF9100	RES,M 910-F-1/4W	
R353	ER0S2THF9100	RES,M 910-F-1/4W	
R354	ERDS2TJ621T	RES,C 620-J-1/4W	
R355	ERDS2TJ621T	RES,C 620-J-1/4W	
R356	ERDS2TJ621T	RES,C 620-J-1/4W	
R357	ERDS2TJ102T	RES,C 1K-J-1/4W	
R358	ERDS1TJ134T	RES,C 130K-J-1/2W	
R359	ERDS1TJ134T	RES,C 130K-J-1/2W	
R360	ERDS1TJ134T	RES,C 130K-J-1/2W	
R361	ER0S2THF8451	RES,M 8.45K-F-1/4W	
R362	ER0S2THF2001	RES,M 2K-F-1/4W	
R363	ERC12GK102D	RES,C 1K-K-1/2W	
R364	ERC12GK102D	RES,C 1K-K-1/2W	

R365	ERC12GK102D	RES,C 1K-K-1/2W	
R369	ERDS2TJ393T	RES,C 39K-J-1/4W	
R371	ERDS2TJ102T	RES,C 1K-J-1/4W	
R372	ERDS2TJ102T	RES,C 1K-J-1/4W	
R374	ERQ12AJ121P	RES,F 120-J-1/2W	
R375	ERDS2TJ222T	RES,C 2.2K-J-1/4W	
R401	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R402	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R403	ERJ6GEYJ622V	RES,M 6.2K-J-1/10W	
R404	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R405	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R410	ERJ6ENF2492V	RES,M 24.9K-F-1/10W	
R412	ERJ6ENF6202V	RES,M 62K-F-1/10W	
R450	ERDS2TJ821T	RES,C 820-J-1/2W	
R451	ERG2FJ221H	RES,M 220-J-2W	
R452	ERDS1FJ6R8T	RES,C 6.8-J-1/2W	
R453	ER0S2THF1202	RES,M 12K-F-1/4W	
R454	ERDS2TJ182T	RES,C 1.8K-J-1/4W	
R455	ERDS2TJ512T	RES,C 5.1K-J-1/4W	
R456	ERDS2TJ182T	RES,C 1.8K-J-1/4W	
R457	ERDS2TJ112T	RES,C 1.1K-J-1/4W	
R458	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R459	ERX1SJ1R2P	RES,M 1.2-J-1W	
R460	ER0S2THF1002	RES,M 10K-F-1/4W	
R461	ER0S2THF1501	RES,M 1.5K-F-1/4W	
R465	ERJ6GEYJ104V	RES,M 100K-J-1/10W	
R468	ERJ6GEYJ104V	RES,M 100K-J-1/10W	
R469	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R470	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R471	ERJ6GEYJ224V	RES,M 220K-J-1/10W	
R472	ERJ6GEYJ123V	RES,M 12K-J-1/10W	
R476	ERJ6GEYJ272V	RES,M 2.7K-J-1/10W	
R480	ERDS2TJ392T	RES,C 3.9K-J-1/4W	
R481	ERDS1FJ1R0T	RES,C 1.0-J-1/2W	

R482	ERDS1FJ1R0T	RES,C 1.0-J-1/2W	
R485	ERJ6GEYJ152V	RES,M 1.5K-J-1/10W	
R486	ERJ6GEYJ473V	RES,M 47K-J-1/10W	
R487	ERJ6GEYJ822V	RES,M 8.2K-J-1/10W	
R489	ER0S2THF1202	RES,M 12K-F-1/4W	
R490	ER0S2THF5101	RES,M 5.1K-F-1/4W	
R491	ER0S2THF1052	RES,M 10.5K-F-1/4W	
R504	ERJ6GEYJ333V	RES,M 33K-J-1/10W	
R505	ERDS1TJ561T	RES,C 560-J-1/2W	
R510	ERG2FJ332H	RES,M 3.30K-J-2W	
R512	ERG3FJ152H	RES,M 1.5K-J-3W	
R513	ERG3FJ152H	RES,M 1.5K-J-3W	
R515	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R516	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R517	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R524	ERG1FJS122D	RES,M 1200-J-1W	
R542	ERJ6GEYJ272V	RES,M 2.7K-J-1/10W	
R547	ERQ1CJPR82S	RES,F .82-J-1W	
R550	ERJ6GEYJ682V	RES,M 6.8K-J-1/10W	
R553	ERG3FJ680H	RES,M 68-J-3W	
R554	ERG3FJ680H	RES,M 68-J-3W	
R556	ERDS1FJ1R0T	RES,C 1.0-J-1/2W	
R557	ERF10ZK2R7	RES,W 2.7-K-10W	
R559	ERG2FJ683H	RES,M 12K-J-2W	
R560	ERDS1FJ1R0T	RES,C 1.0-J-1/2W	
R561	ERDS2TJ103T	RES,C 10K-J-1/4W	
R562	ERDS2TJ272T	RES,C 2.7K-J-1/4W	
R565	ERDS1FJ1R0T	RES,C 1.0-J-1/2W	
R567	ERDS1FJ1R0T	RES,C 1.0-J-1/2W	
R571	ERDS1FJ1R0T	RES,C 1.0-J-1/2W	
R576	ERQ12AJ101P	RES,F 100-J-1/2W	
R580	ERD25FJ4R7P	RES,C 4.7-J-1/4W	
R581	ERJ6ENF1692V	RES,M 16.9K-F-1/10W	
R582	ERJ6ENF4992V	RES,M 49.9K-F-1/10W	

R590	ERDS2TJ473T	RES,C 47K-J-1/4W	
R597	EROS2THF2202	RES,M 22K-F-1/4W	
R601	ERJ6GEYJ391V	RES,M 390-J-1/10W	
R606	ERJ6GEYJ222V	RES,M 2.2K-J-1/10W	
R613	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R614	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R618	ERJ6GEYJ474V	RES,M 470K-J-1/10W	
R619	ERJ6GEYJ563V	RES,M 56K-J-1/10W	
R620	ERJ6GEYJ333V	RES,M 33K-J-1/10W	
R701	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R702	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R704	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R705	ERJ6GEYJ332V	RES,M 3.3K-J-1/10W	
R706	ERJ6GEYJ161V	RES,M 160-J-1/10W	
R707	ERJ6GEYJ561V	RES,M 560-J-1/10W	
R708	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R709	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R710	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R711	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R712	ERJ6GEYJ222V	RES,M 2.2K-J-1/10W	
R713	ERJ6GEYJ822V	RES,M 8.2K-J-1/10W	
R714	ERDS1FJ102T	RES,C 1K-J-1/2W	
R716	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R717	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R720	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R752	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R753	ERDS1FJ102T	RES,C 1K-J-1/2W	
R754	ERDS1TJ751T	RES,C 750-J-1/2W	
R756	ERG2FJ820H	RES,M 82-J-2W	
R757	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R801	ERF7ZK1R5	RES,W 1.5-K-7W	
R804	ERDS2TJ182T	RES,C 1.8K-J-1/4W	
R805	ERG2FJ100H	RES,M 10-J-2W	
R806	ERDS2TJ473T	RES,C 47K-J-1/4W	

R807	ERD50FJ334P	RES,C 330K-J-1/2W	
R808	ERD50FJ334P	RES,C 330K-J-1/2W	
R809	ERDS2TJ561T	RES,C 560-J-1/4W	
R811	EROS2THF2611	RES,M 2.61K-F-1/4W	
R812	ERDS2TJ331T	RES,C 330-J-1/4W	
R813	ERDS2TJ223T	RES,C 22K-J-1/4W	
R815	ERC12ZGM825D	RES,S 8.2MEG-M-1/2	
R820	ERJ6GEYJ273V	RES,M 27K-J-1/10W	
R821	ERJ6GEYJ272V	RES,M 2.7K-J-1/10W	
R822	ERDS1FJ102T	RES,C 1K-J-1/2W	
R823	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R826	ERDS2TJ104T	RES,C 100K-J-1/4W	
R827	ERDS2TJ183T	RES,C 18K-J-1/4W	
R828	ERDS2TJ104T	RES,C 100K-J-1/4W	
R829	ERX12SJR47P	RES,M .47-J-1/2W	
R838	EROS2THF2201	RES,M 2.2K-F-1/4W	
R839	EROS2THF1003	RES,M 100K-F-1/4W	
R843	ERDS2TJ271T	RES,C 270-J-1/4W	
R844	ERDS2TJ222T	RES,C 2.2K-J-1/4W	
R845	ERDS2TJ334T	RES,C 330K-J-1/4W	
R849	EROS2THF2002	RES,M 20K-F-1/4W	
R850	ERQ12HJR56P	RES,F .56-J-1/2W	
R851	ERX12SJR47P	RES,M .47-J-1/2W	
R852	ERX2ANJ2R2H	RES,M 2.2-J-2W	
R853	ERX2ANJ2R2H	RES,M 2.2-J-2W	
R854	ERX2ANJ2R2H	RES,M 2.2-J-2W	
R856	ERQ3CJ3R9	RES,F 3.9-J-3W	
R857	ERJ6GEYJ223V	RES,M 22K-J-1/10W	
R858	ERJ6GEYJ272V	RES,M 2.7K-J-1/10W	
R861	ERDS2TJ103T	RES,C 10K-J-1/4W	
R862	ERDS2TJ104T	RES,C 100K-J-1/4W	
R863	ERJ6GEYJ393V	RES,M 39K-J-1/10W	
R864	ERDS2TJ104T	RES,C 100K-J-1/4W	
R901	ERJ6GEYJ473V	RES,M 47K-J-1/10W	









R902	ERJ6GEYJ473V	RES,M 47K-J-1/10W	
R903	ERJ6GEYJ561V	RES,M 560-J-1/10W	
R904	ERJ6GEYJ152V	RES,M 1.5K-J-1/10W	
R905	ERJ6GEYJ391V	RES,M 390-J-1/10W	
R951	ERDS2TJ821T	RES,C 820-J-1/4W	
R952	ERDS2TJ153T	RES,C 15K-J-1/4W	
R953	ERDS2TJ332T	RES,C 3.3K-J-1/4W	
R954	ERDS2TJ431T	RES,C 430-J-1/4W	
R956	ERDS2TJ121T	RES,C 120-J-1/4W	
R958	ERDS2TJ391T	RES,C 390-J-1/4W	
R959	ERDS2TJ101T	RES,C 100-J-1/4W	
R960	ERQ14AJ100E	RES,F 10-J-1/4W	
R961	ERQ1CJP331S	RES,F 330-J-1W	
R962	ERDS2TJ330T	RES,C 33-J-1/4W	
R963	ERDS2TJ330T	RES,C 33-J-1/4W	
R964	ERDS2TJ471T	RES,C 470-J-1/4W	
R965	ERDS2TJ563T	RES,C 56K-J-1/4W	
R966	ERDS1FVJ471T	RES,C 470-J-1/4W	
R967	ERDS2TJ563T	RES,C 56K-J-1/4W	
R968	ERDS2TJ471T	RES,C 470-J-1/4W	
R969	ERDS2TJ390T	RES,C 39-J-1/2W	
R970	ERDS2TJ2R2T	RES,C 2.2-J-1/4W	
R971	ERDS2TJ2R2T	RES,C 2.2-J-1/4W	
R972	ERDS2TJ390T	RES,C 39-J-1/2W	
R973	ERDS2TJ101T	RES,C 100-J-1/4W	
R974	ERDS2TJ333T	RES,C 33K-J-1/4W	
R975	ERDS2TJ101T	RES,C 100-J-1/4W	
R976	ERDS2TJ101T	RES,C 100-J-1/4W	
R977	ERDS2TJ561T	RES,C 560-J-1/4W	
R978	ERDS2TJ101T	RES,C 100-J-1/4W	
R987	ERDS2TJ472T	RES,C 4.7K-J-1/4	
R988	ERDS2TJ331T	RES,C 330-J-1/4W	
R989	ERDS2TJ682T	RES,C 6.8K-J-1/4W	
R990	ERDS2TJ471T	RES,C 470-J-1/4W	

R993	ERDS2TJ471T	RES,C 470-J-1/4W	
R1010	ERDS2TJ472T	RES,C 4.7K-J-1/4	
R1011	ERDS2TJ103T	RES,C 10K-J-1/4W	
R1012	ERDS2TJ104T	RES,C 100K-J-1/4W	
R1013	ERDS2TJ103T	RES,C 10K-J-1/4W	
R1014	ERDS2TJ103T	RES,C 10K-J-1/4W	
R1015	ERDS2TJ105T	RES,C 1M-J-1/4W	
R1018	ERDS2TJ101T	RES,C 100-J-1/4W	
R1019	ERDS2TJ101T	RES,C 100-J-1/4W	
R1020	ERDS2TJ561T	RES,C 560-J-1/4W	
R1021	ERDS2TJ103T	RES,C 10K-J-1/4W	
R1022	ERDS2TJ101T	RES,C 100-J-1/4W	
R1023	ERDS2TJ101T	RES,C 100-J-1/4W	
R1028	ERDS2TJ103T	RES,C 10K-J-1/4W	
R1033	ERDS2TJ104T	RES,C 100K-J-1/4W	
R1034	ERDS2TJ103T	RES,C 10K-J-1/4W	
R1035	ERDS2TJ103T	RES,C 10K-J-1/4W	
R1036	ERDS2TJ682T	RES,C 6.8K-J-1/4W	
R1037	ERDS2TJ105T	RES,C 1M-J-1/4W	
R1040	ERDS2TJ223T	RES,C 22K-J-1/4W	
R1041	ERDS2TJ562T	RES,C 5.6K-J-1/4W	
R1042	ERDS2TJ102T	RES,C 1K-J-1/4W	
R1043	ERDS2TJ223T	RES,C 22K-J-1/4W	
R1044	ERDS2TJ562T	RES,C 5.6K-J-1/4W	
R1045	ERDS2TJ223T	RES,C 22K-J-1/4W	
R1046	ERDS2TJ562T	RES,C 5.6K-J-1/4W	
R1047	ERDS2TJ102T	RES,C 1K-J-1/4W	
R1048	ERDS2TJ223T	RES,C 22K-J-1/4W	
R1049	ERDS2TJ562T	RES,C 5.6K-J-1/4W	
R2203	ERJ6GEYJ751V	RES,M 750-J-1/10W	
R2206	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R2207	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R2221	ERJ6GEYJ273V	RES,M 27K-J-1/10W	
R2303	ERJ6GEYJ822V	RES,M 8.2K-J-1/10W	

R2304	ERJ6GEYJ822V	RES,M 8.2K-J-1/10W	
R2307	ERJ6GEYJ822V	RES,M 8.2K-J-1/10W	
R2309	ERJ6GEYJ223V	RES,M 22K-J-1/10W	
R2310	ERJ6GEYJ223V	RES,M 22K-J-1/10W	
R2311	ERJ6GEYJ271V	RES,M 270-J-1/10W	
R2312	ERJ6GEYJ153V	RES,M 15K-J-1/10W	
R2313	ERJ6GEYJ153V	RES,M 15K-J-1/10W	
R2316	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R2317	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R2318	ERDS1TJ332T	RES,C 3.3K-J-1/2W	
R2319	ERDS1TJ332T	RES,C 3.3K-J-1/2W	
R2321	ERDS2TJ181T	RES,C 180-J-1/4W	
R2322	ERDS2TJ181T	RES,C 180-J-1/4W	
R2323	ERJ6GEYJ223V	RES,M 22K-J-1/10W	
R2324	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R2325	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R2326	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R2332	ERJ6GEYJ105V	RES,M 1M-J-1/10W	
R2333	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R2334	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R2335	ERJ6GEYJ183V	RES,M 18K-J-1/10W	
R2336	ERJ6GEYJ392V	RES,M 3.9K-J-1/10W	
R2337	ERJ6GEYJ332V	RES,M 3.3K-J-1/10W	
R2338	ERJ6GEYJ332V	RES,M 3.3K-J-1/10W	
R2339	ERJ6GEYJ183V	RES,M 18K-J-1/10W	
R2340	ERJ6GEYJ392V	RES,M 3.9K-J-1/10W	
R2345	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R2346	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R2347	ERJ6GEYJ105V	RES,M 1M-J-1/10W	
R2349	ERJ6GEYJ472V	RES,M 4.7K-J-1/10W	
R2351	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R2352	ERJ6GEYJ562V	RES,M 5.6K-J-1/10W	
R2353	ERJ6GEYJ563V	RES,M 56K-J-1/10W	
R2354	ERJ6GEYJ103V	RES,M 10K-J-1/10W	

R2356	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R2366	ERJ6GEYJ222V	RES,M 2.2K-J-1/10W	
R2367	ERJ6GEYJ222V	RES,M 2.2K-J-1/10W	
R2431	ERJ6GEYJ105V	RES,M 1M-J-1/10W	
R2432	ERJ6GEYJ105V	RES,M 1M-J-1/10W	
R2433	ERJ6ENF4701V	RES,M 4.7K-F-1/10W	
R2434	ERJ6GEYJ681V	RES,M 680-J-1/10W	
R2435	ERJ6ENF3902V	RES,M 39K-F-1/10W	
R2436	ERJ6ENF6202V	RES,M 62K-F-1/10W	
R2437	ERJ6GEYJ681V	RES,M 680-J-1/10W	
R2438	ERJ6GEYJ271V	RES,M 270-J-1/10W	
R2439	ERJ6GEYJ271V	RES,M 270-J-1/10W	
R3001	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R3003	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R3004	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R3005	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R3006	ERJ6GEYJ750V	RES,M 75-J-1/10W	
R3007	ERJ6ENF75R0V	RES,M 75.0-F-1/10W	
R3008	ERJ6GEYJ750V	RES,M 75-J-1/10W	
R3009	ERJ6ENF75R0V	RES,M 75.0-F-1/10W	
R3010	ERJ6ENF75R0V	RES,M 75.0-F-1/10W	
R3011	ERJ6ENF75R0V	RES,M 75.0-F-1/10W	
R3012	ERJ6ENF75R0V	RES,M 75.0-F-1/10W	
R3013	ERJ6GEYJ330V	RES,M 33-J-1/10W	
R3014	ERJ6GEYJ330V	RES,M 33-J-1/10W	
R3015	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R3016	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R3018	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R3019	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R3021	ERJ6GEYJ101V	RES,M 100-J-1/10W	
R3025	ERJ6ENF75R0V	RES,M 75.0-F-1/10W	
R3027	ERJ6ENF75R0V	RES,M 75.0-F-1/10W	
R3027	ERJ6ENF75R0V	RES,M 75.0-F-1/10W	
R3028	ERJ6ENF75R0V	RES,M 75.0-F-1/10W	

R4801	ERDS2TJ472T	RES,C 4.7K-J-1/4	
R4803	ERX12SJ1R0P	RES,M 1.0-J-1/2W	
R4804	ER0S2THF2201	RES,M 2.2K-F-1/4W	
R4805	ER0S2THF2201	RES,M 2.2K-F-1/4W	
R4806	ER0S2THF2201	RES,M 2.2K-F-1/4W	
R4807	ER0S2THF2201	RES,M 2.2K-F-1/4W	
R4808	ER0S2THF3003	RES,M 300K-F-1/4W	
R4809	ER0S2THF1002	RES,M 10K-F-1/4W	
R4810	ER0S2THF1502	RES,M 15.0K-F-1/4W	
R4811	ER0S2THF1002	RES,M 10K-F-1/4W	
R4812	ER0S2THF3301	RES,M 3.3K-F-1/4W	
R4815	ERDS1FJ100T	RES,C 10-J-1/2W	
R6501	ERJ6GEYJ273V	RES,M 27K-J-1/10W	
R6502	ERJ6GEYJ473V	RES,M 47K-J-1/10W	
R6503	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R6504	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R6505	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R6506	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R6509	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R6510	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R6512	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R6513	ERJ6GEYJ122V	RES,M 1.2K-J-1/10W	
R6514	ERJ6GEYJ123V	RES,M 12K-J-1/10W	
R6516	ERJ6GEYJ103V	RES,M 10K-J-1/10W	
R6517	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R6520	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R6522	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R6524	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R6538	ERJ6GEYJ821V	RES,M 820-J-1/10W	
R6548	ERJ6GEYJ471V	RES,M 470-J-1/10W	
R6565	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R6566	ERJ6GEYJ681V	RES,M 680-J-1/10W	
R6567	ERJ6GEYJ102V	RES,M 1K-J-1/10W	
R6568	ERJ6GEYJ102V	RES,M 1K-J-1/10W	

SWITCHES			
S001	EVQPC105K	SWITCH	
S002	EVQPC105K	SWITCH	
S003	EVQPC105K	SWITCH	
S004	EVQPC105K	SWITCH	
S005	EVQPC105K	SWITCH	
S006	EVQPC105K	SWITCH	
S007	EVQPC105K	SWITCH	
TRANSFORMERS			
T501	ETH19Y70AY	TRANSFORMER HORIZONTAL DRIVER	
T551	KFT4AA390F	TRANSFORMER, FLYBACK	
T801	ETS39AG375NC	TRANSFORMER	
CRYSTALS / FILTERS			
X001	TSSA092	CRYSTAL OSCILLATOR	
X501	TSS2AA001	CRYSTAL, 3.58MHZ	
X601	H2A503300008	CERAMIC OSCILLATOR	
OTHERS			
TNR001	ENG36604GR	TUNER	
M001	TSX2AA0212-2	LINE CORD A.C.	
M002	A68QCP893XU	CRT 27 INCH	
M003	K3B10CA00040	SOCKET, CRT	
DY	TLY2AA016	DEFLECTION YOKE	
DEG	TSP2AA026	COIL, DEGAUSSING	
M004	TSP2AF005	COIL, GEOMAGNETIC	
M005	TP-13000PX5	CONVERGENCE YOKE	
M006	TSN63115-4	MAGNET, PURITY	
M007	TXF3A01ZERA	ASSY., DAG GND	
M008	0FMK014ZZ	CONVERGENCE CORRECTOR STRIP	
M009	TAS2AA0023	SPEAKER 8-OHM	
M010	TBLB3056-2	RUBBER SHEET	
M011	TBM2A30843	BADGE, PANASONIC	
M012	TBX2AA0151GA	BUTTON, 7-KEY	
M013	TEK6940	DOOR CATCH	
M014	TKP2AA0615S	DOOR	

M016	TKX2AA0131	GUIDE, IR	
M017	TXFKY25FSER	ASSY, CABINET FRONT CABINET RUBBER BASE, PLASTIC CABINET, FELT, PAPER NAMEPLATE	
M015	TXFKU12FSER	ASSY, CABINET BACK RUBBER BASE, FELT, PAPER NAMEPLATES, PLASTIC BACK CABINET	
JK1001	TJB2AX0021	MODULAR JACK	
JK1002	TJB2AX0051	POWER OUTLET JACK (ULIM)	
JK3001	TJB2AA0221	TERMINAL, A/V 8P	
JK3002	TJB2AA0171	TERMINAL, S-VHS	
JK3003	TJB2AA0371	TERMINAL, FRONT A/V	
JK3005	TJB2AA0211-1	TERMINAL, A/V 2P	
M018	TQB2AA0476-1	OWNERS MANUAL	

[TOP](#) [PREVIOUS](#) [NEXT](#)