



Display

Date: **June 1, 1998**

Subject: **SMOOTHER OPERATING DIODE G2**

Model: **PVM-95, PVM-96, PVM-97, PVM-135
 PVM-136, PVM-137**

Serial No: **1,000,001–1,007,868 (PVM-95)
 1,000,001–1,004,306 (PVM-96)
 1,000,001–1,009,913 (PVM-97)
 1,000,001–1,002,000 (PVM-135)
 1,000,001–1,001,216 (PVM-136)
 1,000,001–1,003,416 (PVM-137)**

DESCRIPTION

Board heats up if diode G2 begins to fail. To remedy this, perform the following modification procedure.

PARTS REQUIRED

Part No.	Description	Qty.
9-880-220-01	Diode, RGP10K	1
1-214-126-00	Resistor, 560Ω,1/4W	1

MODIFICATION PROCEDURE

For models shown in Table 1, remove and install in their place the applicable components.

Table 1.

Model	Remove	Install
PVM-96	D506 FR106 R518 10Ω 1/4W	Diode RGP10K Res 560Ω 1/4W
PVM-97		
PVM-136		
PVM-137		
PVM-95	D406 FR106	Diode RGP10K
PVM-135	R410 10Ω 1/4W	Res 560Ω 1/4W